



# DIGITAL TIMER

## 4 PIN & 5 PIN



CE  
ISO9001



LED  
Power  
Indicator



Input voltage  
200 ~ 250 VAC



### TECHNICAL DETAILS

Input voltage	200 ~ 250 VAC Frequency 50/60Hz
Contact	Single Throw 30 A, 250 V AC or 20 A, 30V DC
Running Accuracy	± 1 second / day at 20°C
Minimum Time Setting	1 minute
Load	Resistive 30A, Inductive 20A
Memory Back up	Lithium battery inside the timer



## Features

- 16 ON / OFF programs can be set per day
- Easy to replace battery CR2032
- Option to select Day/Days of the week on which the programmed functions to be performed
- LED Power Indicator
- Manual over ride switch
- LCD on screen displays ON and OFF switching status  
With Replace Lithium battery CR2032, inside for memory back up
- With daily weekly and impulse programs
- 4 PIN & 5 PIN Time Switch With LCD Display
- Easy Connection

## Additional Information

- This 24 hour timer switch suitable for water heater, Water dispensers, Street lamp, Staircase lamp, Advertising lamp boxes, Breed aquatics, Irrigation ,Agriculture, Office power auto control, in anywhere need time control in civilian, home or industrial, etc.
- It can be used to set 16 programs to control ON and OFF of electric appliance in 24 hours. It can be programmed to avoid the peak of power, and it can distribute power in time limit to save energy.
- Incorrect wiring / installation can cause electrical fires, injuries, and fatalities.
- 'Don't Die for DIY' Use an RCCB (residual current device). An RCCB can save your life by cutting off the power in the event of an electrical fault caused by a DIY blunder.